



APPLICATION

Linear outlines, architectural detail, back lighting, display lighting, signage, party and event lighting

ROPELIGHT

12V - 24V - 120V
Incandescent - LED

Incandescent Ropelight

	NK-120V-xx	120V Ropelight (0.48W/ft)	Subminiature Lamps 25,000hrs 12 lamp/ft
	LNK-24V-xx	24V Ropelight (0.32W/ft)	
	LNK-12V-xx	12V Ropelight (0.32W/ft)	

LED Ropelight

	LED-120V-xx	120V LED Ropelight	0.15W LED Lamps Up to 70,000hrs 1W/ft 12 lamp/ft
	LED-24V-xx	24V LED Ropelight	
	LED-12V-xx	12V LED Ropelight	

Accessories

	C12-xx		C14-xx
	Mounting Clips		Mounting Channel
	C-Y-13		C5W-xx
	Y cord (5ft 1.5m)		Splice Connector
	C-T		C-X
	T Junction		X Junction
	C-L		LED-SP
	L Junction		LNK-SP
	NK-TK		Standard Parts Pack
	LED-TK		
	Cap		
			Direct power cord (120V)



Type	Voltage	Power Usage	Cutting Increments	Current	Lamp Quantities	Luminosity	Colour	Max run length
NK-120V-CL	120V	5.5W/ft 0.48W/ lamp	18" (red, green, blue, yellow)	46mA/ft	12/ft	6lm/ft	Clear	100ft
NK-120V-xx	120V	5.5W/ft 0.48W/ lamp	24"	46mA/ft	12/ft	6lm/ft	Clear	100ft
LNK-24V-CL (*)	24V	3.85W/ ft 0.32W/ lamp	12" to 48"	160mA/ft	12/ft 6/ft 4/ft 3/ft	5lm/ft	Clear	30ft
LNK-12V-CL	12V	3.85W/ft 0.32W/ lamp	6" to 24"	320mA/ft	12/ft	5lm/ft	Clear	12ft
LED-120V-xx	120V	1W/ft 0.08W/ LED	36"		12/ft	7.5lm/ft	Green/ Blue/ White	180ft
LED-120V-xx	120V	0.5W/ft 0.08W/ LED	60"		12/ft	7.5lm/ft	Red/ Yel- low	300ft
LED-24V-xx	24V	1W/ft	6"		12/ft	7.5lm/ft	Green/ Blue/ White	100ft
LED-24V-xx	24V	0.5W/ft	12"	5lm/ft	12/ft	7.5lm/ft	Red/ Yel- low	150ft
LED-12V-xx	12V	1W/ft	3"		12/ft	7.5lm/ft	Green/ Blue/ White	45ft
LED-12V-xx	12V	0.5W/ft	6"	7.5lm/ft	12/ft	7.5lm/ft	Red/ Yel- low	75ft

(*) Available 1", 2", 3", 4" o.c. lamp spacing